










	<p>MR752-BP</p> <p>Manufacturer Part Number: MR752-BP</p> <hr/> <p>Manufacturer/Brand: microEngineering Labs Inc.</p> <hr/> <p>Part of Description: DIODE GEN 200V 6A LEADED BUTTON</p> <hr/> <p>Datasheets:  MR752-BP.pdf</p> <hr/> <p>RoHS Status:  Lead free / RoHS</p> <hr/> <p>Stock Condition: Compliant New original, 2682 pcs Stock Available.</p> <hr/> <p>Ship From: Hong Kong</p> <hr/> <p>Shipment Way: DHL/Fedex/TNT/UPS/EMS</p>
 <p>Not Actual Photo YIC International Co., Limited.</p>	
<p>Image may be representation. See specs for product details.</p>	

Specifications

Part Number	MR752-BP
Manufacturer	microEngineering Labs Inc.
Description	DIODE GEN 200V 6A LEADED BUTTON
Category	Discrete Semiconductor Products > Diodes - Rectifiers -
Part Status	2682 pcs Stock
Voltage - Peak Reverse (Max)	Standard
Voltage - Forward (Vf) (Max) @ If	6A
Voltage - Breakdown	Leaded Button
Series	-
RoHS Status	Bulk
Reverse Recovery Time (trr)	Standard Recovery >500ns, > 200mA (Io)
Resistance @ If, F	-
Polarization	Button, Axial
Other Names	MR752-BPMS
Mounting Type	Through Hole
Moisture Sensitivity Level (MSL)	1 (Unlimited)
Manufacturer Part Number	MR752-BP
Expanded Description	Diode Standard 200V 6A Through Hole Leaded Button
Diode Configuration	25µA @ 200V
Description	DIODE GEN 200V 6A LEADED BUTTON
Current - Reverse Leakage @ Vr	900mV @ 6A
Current - Average Rectified (Io) (per Diode)	200V
Capacitance @ Vr, F	-65°C ~ 175°C

You May Be Also Be interested

In:

 <p>MR751RLG ON Semiconductor DIODE GP 100V 6A MICRODE BUTTON</p>	 <p>MR752RL ON Semiconductor DIODE GP 200V 6A MICRODE BUTTON</p>	 <p>MR752G ON Semiconductor DIODE GP 200V 6A MICRODE BUTTON</p>	 <p>MR752G ON Semiconductor DIODE GP 200V 6A MICRODE BUTTON</p>
 <p>MR752 ON Semiconductor DIODE GP 200V 6A MICRODE BUTTON</p>	 <p>MR752RLG ON Semiconductor DIODE GP 200V 6A MICRODE BUTTON</p>	 <p>MR752 ON Semiconductor DIODE GP 200V 6A MICRODE BUTTON</p>	 <p>MR752-BP Micro Commercial Co DIODE GEN 200V 6A LEADED BUTTON</p>

MR752-BP Related keyword

More

MR752-BP microEngineering Labs Inc.	MR752-BP Data Sheet	MR752-BP Datasheets	MR752-BP PDF	microEngineering Labs Inc. MR752-BP
MR752-BP Electronic	MR752-BP Components	MR752-BP Distributor	MR752-BP Image	MR752-BP Part
MR752-BP Price	MR752-BP Manufacturer	MR752-BP Picture	MR752-BP Stock	MR752-BP Inventory
MR752-BP New	MR752-BP Original	MR752-BP Warranted	MR752-BP RFQ	MR752-BP Order Online

Contact us: Info@YIC-Electronics.com

ADD: Unit A5-B5 No.509, 5/F Sing Win Factory Building, 15-17 Shing yip St, Kwun Tong, Kowloon, HongKong.

Copyright © 2023 YIC-Electronics.com - YIC International Co., Limited