









	<h2 style="color: red;">ENW-F9202A1EF</h2>	
	<b>Manufacturer Part Number:</b>	ENW-F9202A1EF
	<b>Manufacturer/Brand:</b>	Panasonic
	<b>Part of Description:</b>	PAN9026, WI-FI DUAL BAND 2.4/5 G
	<b>Datasheets:</b>	<a href="#">1.ENW-F9202A1EF.pdf</a> <a href="#">2.ENW-F9202A1EF.pdf</a> <a href="#">3.ENW-F9202A1EF.pdf</a>
<p>Image may be representation. See specs for product details.</p>	<b>RoHS Status:</b>	 Lead free / RoHS
	<b>Stock Condition:</b>	Compliant New original, 2571 pcs Stock Available.
	<b>Ship From:</b>	Hong Kong
	<b>Shipment Way:</b>	DHL/Fedex/TNT/UPS/EMS

### Specifications

Part Number	ENW-F9202A1EF
Manufacturer	Panasonic
Description	PAN9026, WI-FI DUAL BAND 2.4/5 G
Category	RF/IF and RFID > RF Transceiver Modules
Part Status	2571 pcs Stock
Voltage - Supply	1.8 V ~ 3.3 V
Utilized IC / Part	88W8977, ENWF9201AZEF, PAN9026
Series	-
Serial Interfaces	JTAG, UART
Sensitivity	-98dBm
RF Family/Standard	Bluetooth, WiFi
Protocol	802.11a/b/g/n, Bluetooth v5.0
Power - Output	16dBm
Package / Case	51-SMD Module
Other Names	ENWF9202A1EF
Operating Temperature	-30°C ~ 85°C
Mounting Type	Surface Mount
Moisture Sensitivity Level (MSL)	3 (168 Hours)
Modulation	CCK, DSSS, OFDM
Memory Size	-
Manufacturer Standard Lead Time	16 Weeks
Lead Free Status / RoHS Status	Lead free / RoHS Compliant
Frequency	2.4GHz, 5GHz
Data Rate	150Mbps
Current - Transmitting	400mA
Current - Receiving	70mA
Antenna Type	Integrated, Chip

### You May Be Also Be interested

In:

 <p><b>ENW-F9101A1JF</b> Panasonic Electronic Components RF TXRX MOD BLUETOOTH/WIFI CHIP</p>	 <p><b>ENW2-EW10/GRA</b> JKL Components Corp. LAMP INCAND T1.5 NEO WEDGE 14V</p>	 <p><b>ENW-F9201A1EF</b> Panasonic PAN9026, WI-FI DUAL BAND 2.4/5 G</p>	 <p><b>ENW1-EW87</b> JKL Components Corp. LAMP INCAND T1.5 NEO WEDGE 14V</p>
 <p><b>ENW-F9101C1JF</b> Panasonic Electronic Components RF TXRX MOD BLUETOOTH/WIFI</p>	 <p><b>ENW1-EW10</b> JKL Components Corp. LAMP INCAND T1.5 NEO WEDGE 14V</p>	 <p><b>ENW-F9101C1EF</b> Panasonic Electronic Components RF TXRX MOD BLUETOOTH/WIFI</p>	 <p><b>ENW-F9101A1EF</b> Panasonic Electronic Components RF TXRX MOD BLUETOOTH/WIFI CHIP</p>

### ENW-F9202A1EF Related keyword

More

ENW-F9202A1EF Panasonic	ENW-F9202A1EF Data Sheet	ENW-F9202A1EF Datasheets	ENW-F9202A1EF PDF	Panasonic ENW-F9202A1EF
ENW-F9202A1EF Electronic	ENW-F9202A1EF Components	ENW-F9202A1EF Distributor	ENW-F9202A1EF Image	ENW-F9202A1EF Part
ENW-F9202A1EF Price	ENW-F9202A1EF Manufacturer	ENW-F9202A1EF Picture	ENW-F9202A1EF Stock	ENW-F9202A1EF Inventory
ENW-F9202A1EF New	ENW-F9202A1EF Original	ENW-F9202A1EF Warranted	ENW-F9202A1EF RFQ	ENW-F9202A1EF Order Online

Contact us: [Info@YIC-Electronics.com](mailto:Info@YIC-Electronics.com)

ADD:Unit A5-B5 No.509, 5/F Sing Win Factory Building, 15-17 Shing yip St, Kwun Tong, Kowloon, HongKong.

Copyright © 2023 YIC-Electronics.com - YIC International Co., Limited